

DMX CHANNELS

LED FD Fresnel -5 CH Mode (Standard channel model)

Channel	Data	Function	Mark
1	0~255	dimmer	0-255 linear dimmer
2		speed of dimmer	
	0~9	speed of dimmer 2	Default
	10~29	Turn off speed of dimmer	speed of dimmer 4 (the slowest and softest)
	30~69	speed of dimmer 1	
	70~129	speed of dimmer 2	
	130~189	speed of dimmer 3	
	190~255	speed of dimmer 4	
3	0~10		no strobe
	11~255		the speed of strobe (255 is the fastest)
4	0-255		focus
5	0-255		Speed of focus (255 is the fastest)

2 CH Mode (Basic channel model)

channel	data	Function	Mark
1	0~255	Dimmer	0-255 linear dimmer
2	0~255		focus